
Subject: Eminence 12LT Pi BR Qestion

Posted by [Observator](#) on Tue, 04 Sep 2001 14:31:25 GMT

[View Forum Message](#) <> [Reply to Message](#)

Hi again,I'm sorry but i can't find the rightdimensions of Pi-BR for Eminence 12LT...Could you send me, please, a rightdimension of the box and of the BR ?What's also the f3 for this design ?Thanks a lot,O'tor

Subject: Theater Series three Pi

Posted by [Wayne Parham](#) on Tue, 04 Sep 2001 14:44:54 GMT

[View Forum Message](#) <> [Reply to Message](#)

If you are talking about the Delta 12LF, the cabinet to use is the Theater Series three Pi.

Subject: Re: Theater Series three Pi

Posted by [Observator](#) on Tue, 04 Sep 2001 15:27:02 GMT

[View Forum Message](#) <> [Reply to Message](#)

Hi Wayne,Unfortunately not. Its not Delta 12LF. It Is Beta 12LT used in Thorsten Afterburner project. There was a post from you in another forum about a Pi-align for this driver, and i just can't find the details.Thanks in advance,O'Tor

Subject: Beta 12LT in PiAlign'ed cabinet

Posted by [Wayne Parham](#) on Tue, 04 Sep 2001 23:56:57 GMT

[View Forum Message](#) <> [Reply to Message](#)

You asked what Pi Alignments recommend for the Eminence Beta 12LT speaker. Eminence publishes the following specifications: $V_{as} = 4.81$ cubic feet $F_{ts} = 45\text{Hz}$ $Q_{ts} = 0.51$ And these correspond to PiAlign values of: $V_{ad} = 4.81$ cubic feet $F_{rd} = 45\text{Hz}$ $Q_d = 2.0$ (1/ Q_{ts})PiAlign recommends a bass reflex cabinet of 2.4 cubic feet tuned to 33.75Hz and having Q of 1.5. It recommends doing this using a 2.5" diameter port that's 2.75" long, which is very close to a perfect match - corresponding to F_{rd} of 34.0Hz and Q of 1.56. Without any volume displacements, it is suggesting the cabinet be 24" x 16" x 11", but after consideration of the volume displaced by the speaker driver and the wood thickness, I'd expect your cabinet's outside dimensions to be closer to 26" x 18" x 14". And while these cabinet dimensions can be off a half

inch or so, be sure the port dimensions are "right on the money." You must have inside dimensions of 2.5" diameter and 2.75" long for the design to be optimal.

Subject: Re: Thanks a lot ! (nt)
Posted by [Observator](#) on Wed, 05 Sep 2001 05:19:55 GMT
[View Forum Message](#) <> [Reply to Message](#)

nt

Subject: Good luck and keep us posted!
Posted by [AudioLapDance](#) on Wed, 05 Sep 2001 09:44:42 GMT
[View Forum Message](#) <> [Reply to Message](#)

Hi Observator, Hey, who you lookin at! ;-)| built Thorsten's Afterburner but am now going to try the Beta12LT in a PI cabinet. Thorsten used an Extended Bass Shelf alignment (EBS) which is in the oposite direction compared to Wayne's alignment. It should make a nice comparison. Do you have the Rat Shack tweet? I found them too bright--could be too sensitive or the 1st order crossover isn't attenuating quickly enough so there's too much overlap at 8-10kHz. I'm going try a piezo tweet with a second order crossover. Good luck and please let us know how it goes, Cheers, Jeff

Subject: Re: Good luck and keep us posted!
Posted by [Observator](#) on Wed, 05 Sep 2001 10:23:16 GMT
[View Forum Message](#) <> [Reply to Message](#)

Hi Jeff, > I built Thorsten's Afterburner but am now going to try the Beta12LT > in a PI cabinet. From my side, I was inspired by reviews about hammer dynamic super12. I haven't possibility to hear it, so i decided first to build afterburners for having an idea how 12" FR performs. what's your opinion ? Can you compare it with something I know ;-), let say FE103 or 40-1354 or FE208s....what's also your amplifier ?> Do you have the Rat Shack tweet? I found them too bright--could be > too sensitive or the 1st order crossover isn't attenuating quickly > enough so there's too much overlap at 8-10kHz.> I'm going try a piezo tweet with a second order crossover. Thanks for your advice, i haven't possibility to buy RS tweeter here so I had the same idea as you - Motorola piezo. Which one is your favorite ? And, what about adding a low-pass and zobel for beta12tl same as used in super12 ? This could be a solution to clarify the 10k region.> Good luck and please let us know

how it goes,> Cheers,> Jeff thanks, I will doO'Tor

Subject: Re: Beta 12LT in PiAlign'ed cabinet
Posted by [Observator](#) on Wed, 26 Sep 2001 14:10:37 GMT
[View Forum Message](#) <> [Reply to Message](#)

Hi Wayne,> PiAlign recommends a bass reflex cabinet of 2.4 cubic feet tuned to > 33.75Hz and having Q of 1.5. It recommends doing this using a 2.5" > diameter port that's 2.75" long, which is very close to a perfect > match - corresponding to Frd of 34.0Hz and Q of 1.56. I just verified this calculs and unfortunately this doesn't workfor me. In your whitepaper for the port calculation I read:Fre = $1/(2*\pi)*(Ap/(Ve*Lc))^{(1/2)}$ If Dp=2.5 and Lp=2.75, then Lc= 4.87, if Dp=2.5 then $Ap=\pi*(Dp/2)^2 = 4.91$,and then for Ve=2.4 i haveFre = 0.10312and not 33.75 Hz as you said.(Qe = 1.54 with no problem)What's wrong ?Thanks in advance,O'Tor

Subject: Re: Beta 12LT in PiAlign'ed cabinet
Posted by [Wayne Parham](#) on Fri, 28 Sep 2001 20:15:19 GMT
[View Forum Message](#) <> [Reply to Message](#)

You used 2.4 as as cabinet volume but you should have used 2.4 x 1728 to convert it to cubic inches. You must use the same terms throughout - If inches in one place then inches must be used everywhere. You can use feet if you wish, but then the port dimensions must be in feet for "Lc" and sq. feet for "Ap".