

---

Subject: alright then...

Posted by [PakProtector](#) on Tue, 21 Dec 2004 22:41:47 GMT

[View Forum Message](#) <> [Reply to Message](#)

---

Hey-Hey!!!, Seems reasonable... Take a slightly smaller simpler means of doing it. 180vac( or thereabouts, there is a 190-0190 Hammond, 2 or 369EX ), double for a CT winding or a full bridge on a single... hybrid bridge, SF4007 diodes to ground and a 6CA4 for the forward diodes. The same 30 Hy Hammond, and an eBay-ed motor run of 240vac rating and ~100 uF. This will get a reasonable B+. The single 6N2540N5 with a reasonable heatsink will also allow the use of another output point, namely the source of the MOSFET. You'll have what is effectively a source follower output buffer. This also simplifies the cathode circuit because the triode still sees a constant current, and no bypass is needed. Use a pot instead of a fixed resistor to set the current. try 10-15 mA. The output coupling cap has already been mentioned. the EX Hammond has 2.5A of 6.3, plenty for a 6CA4 and single 5687. DC can be done with a RadioShack TX and an LM317 should it be required at ~\$20 additional. Biasing of ~3 volts ought to give a good operating point, 2-4v is a good place to play.  $V=iR$ . so, 2 nine pin sockets, 1 5687, 1 6CA4, 1 369EX( note 370AX is on sale for \$36 ), 1 157G, one 80-100 uF/240vac motor run oiler, 2 5 uF motor run caps for the output coupling, 2 6N2540N5 mosfets, 510R 1/4 watt carbon comp gate stoppers, 2 1kOhm pots for current set, 4 RCA jacks, 1 stereo volume control ( R-S 100k Alps is ~\$3 ), 4 red/20 mA LED's for bias, wire and chassis material. so where are we? regards, Douglas....damned Thrintun!

---