

---

Subject: Re: SE 300B Project, Part 13 - The finished amp

Posted by [Damir](#) on Mon, 10 Jul 2006 12:08:46 GMT

[View Forum Message](#) <> [Reply to Message](#)

---

Hi, thanks, and welcome to the forum! We need about 50Vrms (70Vp) to "drive" 300B to the full power. With CCS-ed driver triode (and high impedance 300B grid choke as a load), we have the "driver" amplification practically equal to the  $\mu$ , or theoretical amplification factor (very close). In the case of E180F in triode -  $A = \mu \sim 50$ , or input sensitivity for the full power is 1 Vrms. Although C3g specs said  $\mu \sim 40$ , my "Siemens" tubes have  $\mu \sim 50$ , again - input sens. is 1 Vrms. (If we'd have a tube with "right"  $\mu = 40$  spec, then sens. would be  $50/40 = 1,25$  Vrms). D3a has larger amplification,  $A = \mu \sim 75$ , and then input sensitivity is about 0,7 Vrms. Unfortunately, I have no EC8010, and didn't try them. But, (based on its data) I expect it to be the similar like other high-gm "candidates" above, and others I tried (6C45Pi, E280F trioded). If you have some EC8010 on hands, the best you can do is to try it for yourself. Use CCS,  $I_a \sim 10$  mA,  $R_k = 220$ -250 Ohms bypassed with 220  $\mu$ F (MKP of 100  $\mu$ F at least recommended) - like your starting point. Beware that this tube has g1 connected on five pins... I'd use grid-stop resistor (say 100...220 Ohms, CC) on every input pin. Based on the specs, you can expect  $A = \mu = 60$  times, or input sensitivity of  $50/60 = 0,83$  Vrms. Adjust  $I_a$  (or  $R_k$  if necessary) to have  $U_a$  about 200V. Seriously, only you'd can say about "sound" in your system, and like/dislike factors :-). You can expect rel. large input capacitance, unfortunately. Do you have some parts (tubes, transformers, etc.), or you are still in "various schematics" phase?

---