

---

Subject: Determining mechanical reactance values for Spice models

Posted by [Wayne Parham](#) on Mon, 31 Dec 2001 20:39:03 GMT

[View Forum Message](#) <> [Reply to Message](#)

---

that impedance at resonance is 50 ohms and the resonant frequency is 40Hz with a Q of 5.0, then resistance must 50 ohms and inductive and capacitive reactances must be equal at 40Hz. A similar procedure is used to determine reactance values for the impedance peaks caused by horns, where the frequency and Q of resonant events is not expressly stated. In this case, the impedance graph is used to determine resonant frequency and Q values for each peak that is to be simulated with a corresponding tank circuit. Q is relatively easy to determine - it is resonance divided by bandwidth - so the frequency of each peak is divided by the width of each peak (at 70% amplitude) to determine its Q. This gives you resonant frequency, Q and amplitude, which is everything you need to know to express the reactive nature of a device.