
Subject: PP 2A3 intro

Posted by [PakProtector](#) on Wed, 11 Jan 2006 15:40:19 GMT

[View Forum Message](#) <> [Reply to Message](#)

hey-Hey!!!,The schematic for the PP 2A3 amp is done. Galahad is its name. It employs a Schmitt inverter front end pair of 12BY7 pentodes with neutralizing caps for the 2A3 finals. The 10k load gives a -3dB point of ~23 kHz w/o neutralization. With the caps in place to eliminate the effects of Miller on the grid-anode capacitance, it should run to the limits of the output Iron.To ensure Class A operation, I suggest the uprated 2A3's from Russia. They will also make a little bit more power. This amp ought to do 7W quite well.cheers,Douglas

http://www.audioroundtable.com/GroupBuild/Projects/Galahad_Schematic.pdf

Subject: Re: PP 2A3 intro

Posted by [Wayne Parham](#) on Wed, 11 Jan 2006 16:55:17 GMT

[View Forum Message](#) <> [Reply to Message](#)

What transformer and grid choke does it use?

Subject: Re: PP 2A3 intro

Posted by [Manualblock](#) on Wed, 11 Jan 2006 19:40:38 GMT

[View Forum Message](#) <> [Reply to Message](#)

Also I don't see the CCS?

Subject: More

Posted by [PakProtector](#) on Wed, 11 Jan 2006 20:49:39 GMT

[View Forum Message](#) <> [Reply to Message](#)

Hey-Hey!!!,To the CCS, there are several levels, from the simplest current regulator diodes, to the depletion-mode MOSFET cascode circuit detailed in the original Merlin. I left out the PS as well as the bias supply, so there should be a few additions in the follow-up schematic. I suggest the Merlin MOSFET cascode. It is simple and easy to implement and with -20V. Unfortunately the 2A3 will need ~75 volts negative...I am not sure what to do about that. Perhaps a doubler, and take the CCS to the first half.On the OPTx, I have several to work through. I would hazzard a guess that the Peerless S-230-Q is going to win the tasting. The 2A3's will run this circuit to less than 10W, so it is not too critical about what OPTx, as long as it is able to deal with the 60-70mA of idle per leg.On the grid choke, the HTS-7547 should do quite well. Call for no spacer and minimum-gap

butt stacking to present the pentodes with minimum load.cheers,Douglas

Subject: Re: More

Posted by [Damir](#) on Thu, 12 Jan 2006 15:26:43 GMT

[View Forum Message](#) <> [Reply to Message](#)

A few more details, please - what's the Ia and Ig2 per 12BY7, (and CCS current - the sum of this, x 2 tubes). Then, Rg2 value, $Rg2 = ((B+) - 90) / Ig2$. Did you "breadbord" it and your comments about sound (possible comparisons with "Merlin"?). I noticed that you didn't use "stoppers" on g2 and 2A3 input - not necessary? For HV 15pF cap - maybe three 47pF in series (standard value)? And 23kHz (w/o 15pF caps) means "lot" of Cw (with Zout~10k of the driver)?

Subject: Re: More

Posted by [PakProtector](#) on Thu, 12 Jan 2006 16:13:28 GMT

[View Forum Message](#) <> [Reply to Message](#)

I have not breadboarded it. The g2 dropping R will get set 'in-circuit'. 150R CC resistors for g2 stoppers would probably be a good idea. On idle current, plan on putting the plate V about half way between B+ and g2 (maybe a bit closer to g2). I'd use an adjustable R-set for the cathode CCS, it makes covering for other parameter drifts and variations easier. I have some coax that makes nice capacitors in the few pF range. TFE insulation and everything. Probably going to take 12 cm of it. I also neglected Cw of the choke, and may have dropped a zero in the calculation. cheers, Douglas

Subject: Looks Great !

Posted by [MRCLASSICMAN](#) on Thu, 12 Jan 2006 16:15:58 GMT

[View Forum Message](#) <> [Reply to Message](#)

Looks Sweet ! Keep us posted on the developements , like the grid choke and the -75 volt supply. I have a -200 using Hammonds and two 100 volt zeniers for its -200 volt supply. Few mod's we could get 75 volts no problem. Terry

Subject: Re: More

Posted by [Damir](#) on Fri, 13 Jan 2006 17:17:52 GMT

[View Forum Message](#) <> [Reply to Message](#)

Forgot to ask about sensitivity/amplification of the driver stage. With "polished" details - good project!

Subject: front end gain

Posted by [PakProtector](#) on Fri, 13 Jan 2006 21:30:42 GMT

[View Forum Message](#) <> [Reply to Message](#)

Hey-Hey!!!, Using the traditional $g_m \cdot R_{load}$ and then divide by two and we'll arrive at an answer. g_m is going to be ~10 mA/V; R_{load} is 10k or gain of 100. Divide by two for the differential circuit, and we get V/V of 50 per phase. Looks like a little more than a volt to deliver the 60V or so to the 2A3 grid. We could try a lower load and take a bit away, but remember to raise the g_2 the correct amount to keep a nice clean area to work the load through. The 12BY7 is a nice tube, and the required data to make these g_2 voltage determinations is available. I am tempted to try its DH cousin... :) cheers, Douglas remember also that the grid choke is going to offer an elliptical load at the LF extreme. Lowering the load (to lower numeric) would alleviate that sort of behaviour a bit.

Subject: More front end tubes

Posted by [PakProtector](#) on Sat, 14 Jan 2006 00:40:33 GMT

[View Forum Message](#) <> [Reply to Message](#)

Hey-hey!!!, There are other inexpensive front end pentodes to use. 6AQ5 is one suspect. Put g_2 at 100V for a 10k load and 300V B+. 6CL6 would want a little bit less (if the curves are to be trusted), say ~80V. The 6AQ5 would cut gain by half due to lower g_m , and 6CL6 by maybe a fifth. EF184 data I have found does not show anode current at $g_1=0$ and varying g_2 , but it would offer slightly higher gain than the 12BY7. Guidelines only, play and see how they sound. cheers, Douglas

Subject: and further fun...

Posted by [PakProtector](#) on Mon, 16 Jan 2006 16:00:18 GMT

[View Forum Message](#) <> [Reply to Message](#)

examine some of the other small power tubes. 6W6 and 6EZ5 or 7355 do quite well with 6-8k loads. Adjust with g_2 voltage, and that 2A3 grid doesn't stand a chance of misbehaving. 6W6 is waaaaayyyyyy cheap too, and it looks nice with a g_2 of ~60V or so. That one is on the list for sure! cheers, Douglas
